

# PLE-WP3S2Z-EU Wall Panel

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Can be used for all Plena Easyline (PLE) mixer-amplifiers
- ▶ Remote selection of three music source inputs
- ▶ Remote zone selection
- ▶ Perfect companion to Bosch volume controls
- ▶ Daisy-chain of multiple wall panels

The Plena PLE-WP3S2Z-EU Wall Panel is used to remotely select a music source and activate or deactivate zones of a Plena PLE audio mixer or mixer amplifier.

## Functions

### Remote zone and input source control

Two zones and three music input sources can be controlled from a remote location by selecting the individual switches.

### Indicators

The ON status of each zone and selected music source is indicated by an LED.

### Connections and settings

With the use of CAT-5 cable and RJ-45 connector the PLE-WP3S2Z-EU Wall Panel can be easily and quickly connected to the PLE series mixer or mixer amplifier. Settings are not required.

### Daisy chain / Remote locations

Maximum four PLE-WP3S2Z-EU Wall Panels can be daisy chained to remotely control a PLE series mixer or mixer amplifier.

## Certifications and approvals

Safety	acc. to EN 60065
EMC emission	acc. to EN 55103-1
EMC immunity	acc. to EN 55103-2

## Region Certification

Europe	CE
--------	----

## Installation/configuration notes

The Wall Panel is installed to the mixer or mixer-amplifier via standard CAT-5 cable with RJ-45 connector. The maximum cable distance is 200 m. The design and color are unobtrusive in any interior. Ease of installation, operation and reliability is optimized in the design. The appearance is matched to the Bosch Loudspeaker Volume Controls.

The wall panel buttons have the same function as the corresponding buttons of the Plena mixer front panel

**Parts included**

1	PLE-WP3S2Z-EU Wall Panel
1	Quick Reference Card

**Technical specifications****Electrical**

<b>Power supply</b>	
Voltage range	5 VDC, supplied by the connected amplifier
Current consumption (typical)	<50 mA
<b>Connectors</b>	
to (mixer) amplifier	1 x RJ-45
Loop through	1 x RJ-45

**Mechanical**

Dimensions (H x W x D)	87 x 87 x 21 mm (3.43 x 3.43 x 0.83 in)
Weight	Approx. 0.35 kg (0.77 lb)
Color	White
Label text color	Silver

**Environmental**

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

**Ordering information****PLE-WP3S2Z-EU Wall Panel**

remotely select a music source and activate or deactivate zones of a Plena PLE audio mixer or mixer amplifier

Order number **PLE-WP3S2Z-EU**

**Represented by:****Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
al.securitysystems@bosch.com  
www.boschsecurity.com