

# Plena All-in-One Wall Panel

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Remote control for the Plena All-in-One Unit PLN-6AIO240
- ▶ BGM routing and volume control
- ▶ Remote selection of four music source inputs
- ▶ Remote microphone/line input
- ▶ Powered from the Plena All-in-One Unit

The Plena Wall Panel PLN-4S6Z is used to control the source selection, zone selection, and volume of the Plena All-in-One Unit PLN-6AIO240 from a remote location, and accepts a microphone or music source.

## System overview

The Wall Panel is connected to the Plena All-in-One Unit PLN-6AIO240 with a standard Cat-5 cable. The maximum cable length is 600 m. The buttons on the Wall Panel have the same function as the corresponding buttons on the front panel of the All-in-One Unit. The design and color of the Wall Panel are unobtrusive in any interior. Ease of installation, operation, and reliability are optimized in the design.

## Functions

### Remote zone and music source control

Six zones and four music input sources can be selected from a remote location. The Enable button on the front of the Wall Panel can be pressed to gain instant remote control over the music selection and master volume.

### Indicators

The ON status of each zone and selected music source is indicated by an LED.

## Connections and settings

The Wall Panel can be easily and quickly connected to the Plena All-in-One Unit, by using a Cat-5 cable and RJ45 connectors. Configuration is not necessary.

## Control and indicators

### Front side:

- Selection buttons for six zones with All-call
- Music source selection button
- Master volume control
- Enable button
- Level control for local audio input

### Interconnections

- XLR connector for microphone
- 3.5 mm stereo connector for music source
- RJ45 connector (inside Wall Panel)

## Certifications and approvals

Safety	IEC/EN 60065
EMC	EN 55103-1 EN 55103-2 EN 61000-3-2 EN 61000-3-3
Environment	EN 50581

US	UL 60065 FCC Part 15B
CA	CSA C22.2.60065
CN	CCC
AU/NZ	C-Tick

Region	Certification
Europe	CE

### Installation/configuration notes

#### Remote control

The Wall Panel can be attached to a wall or flat surface by use of the holes in the rear mounting bracket. It is powered from the Plena All-in-One Unit and uses a single Cat-5 cable for interconnection up to 600 m from the All-in-One Unit. No configuration is needed.

### Parts included

Quantity	Component
1	All-in-One Wall Panel
1 m	Cat-5 cable with RJ45 plugs

### Technical specifications

#### Electrical

Power supply	
Voltage range	24 Vdc, supplied by the connected amplifier
Current consumption (typical)	<50 mA
Connector	1 x RJ45 socket (inside Wall Panel)

#### Mechanical

Dimensions (H x W x D)	115 x 115 x 70 mm (4.5 x 4.5 x 2.8 in)
Weight	Approx. 0.6 kg (1.3 lb)

#### Environmental

Operating temperature	-10°C to +45°C (14°F to +113°F)
Storage temperature	-40°C to +70°C (-40°F to +158°F)
Relative humidity	<95% (non-condensing)

### Ordering information

#### Plena All-in-One Wall Panel

Wired remote control for the Plena All-in-One Unit with local audio inputs.

Order number **PLN-4S6Z**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com